

Combo CAT6 LCD Console Drawers

Optimize rack space. Maximize rack monitoring



CAT6 KVM Dongle-USB&VGA (DGU)



DVI changer



HDMI changer



DP changer



Features


- Support combo interface, VGA-USB & VGA-PS/2.
- Additional one USB Local console to add local KB/Mouse & VGA.
- Up to 40 meters between Servers to KVM.
- Durable 104-key keyboard and touch pad.
- Quick and simple installation.
- Self-locking and auto release rails for ultra convenience.
- Port selection via push buttons or On-Screen-Display (OSD).
- Dedicated daisy chain port to expand up to 256 servers.



Rear of KVM-1708/1908ASL-M6/ULC



Rear of KVM-1716/1916ASL-M6/ULC



Rear of KVM-1732/1932ASL-M6/ULC

Part No.	KVM-1708ASL-M6/ULC	KVM-1716ASL-M6/ULC	KVM-1732ASL-M6/ULC	KVM-1908ASL-M6/ULC	KVM-1916ASL-M6/ULC	KVM-1932ASL-M6/ULC
Direct no. of Computers	8	16	32	8	16	32
Maximum no. of Computers	232(Daisy Chain)	240(Daisy chain)	256(Daisy chain)	232(Daisy Chain)	240(Daisy chain)	256(Daisy chain)
LCD	Size	17"		19"		
	Backlight	LED		LED		
	Resolution	1280*1024		1280*1024		
	Max. color	16.7M		16.7M		
	Luminance	250cd/m2		250cd/m2		
	View Angel (H/V)	176 / 170		170 / 160		
	Contrast Ratio	1000 : 1		1000 : 1		
Port Selection	Push Button, OSD or Hotkey					
USB Local console	Yes , USB x2 for KB/ Mouse , VGA x1					
Max. Computer Distance	40 meters (Servers to KVM)					
KB/Mouse Emulation	USB & PS2					
Rack Depth	500mm to 1100mm (rack cabinet front rails to rear rails)					
Power	100-240V AC 50/60Hz via IEC Type power cord					
Environment	Operation temp: 0 to 50°C Storage temp: -20 to 60°C Humidity: 10% - 90%, non-condensing Shock: 10G acceleration (11ms duration) Vibration: 17 to 500Hz 1G PTP					
Physical Dimensions / Net Weights	448x42x580mm (WxHxD) / 12.0KG			448x42x580mm (WxHxD) / 12.5KG		
Packing Dimensions / Gross weights	715x140x780mm (WxHxD) / 18.0KG			715x140x780mm (WxHxD) / 18.5KG		
Accessory						
1.8meter IEC Type Power Cord						
Option Relate Item						
DGU	CAT6 KVM Dongle-USB&VGA		DVI changer	DVI-to-VGA changer		
DP changer	DisplayPort-to-VGA changer		HDMI changer	HDMI-to-VGA changer		